

Installation instructions : Shaver Socket SY9660CC

Thank you for purchasing this SycamoreLED.com product. Please make sure instructions are followed carefully prior to and during installation and product is not altered, otherwise warranty may not be valid. For technical support or warranty information please visit www.sycamoreLED.com, or call our dedicated technical helpline +44 (0) 113 2866686.

IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) This product should be installed and wired by a qualified electrician in accordance with the current IEE regulations and must be protected by a RCD device.
- 3) Ensure the power supply is disconnected before proceeding with the installation
- 4) This product must be earthed
- 5) All bare earth wires must be covered with appropriate green/yellow sleeving, not supplied
- 6) Please check with manufacturers instruction for suitability with rechargeable shavers

INSTALLATION

- 1) This shaver supply unit is suitable for surface mounting, using a 49mm 2 gang surface back box or flush mounting using a 47mm 2 gang metal back box
- 2) Remove and retain the 2 fixing screws located at the back of the fascia plate
- 3) Feed supply cable through the appropriate knockout installation box. In the case of a metal back box fit a 20mm rubber grommet
- 4) Strip outer sheath of supply cable to suitable length and then remove 10mm of the insulation from the Live (brown) and Neutral (blue) conductors to expose inner cores
- 5) Insert Neutral (blue) conductor into the terminal marked N and fully tighten the screw
- 6) Insert Live (brown) conductor into the terminal marked L and fully tighten the screw
- 7) Insert the earth conductor, ensuring it has been sleeved with green/yellow sleeving, into the terminal marked
- 8) Ensure that an additional earth cable is connected between the shaver supply unit earth terminal and the earth terminal in the back box being used
- 9) Fit socket to back box with the 2 fixing screws provided
- 10) Re-fit the supply fuse (if removed) for isolation and switch supply back on

-Select voltage required 115V/230V by inserting shaver plug into the appropriate socket

-Always unplug appliance after use

DIAGRAM

